Data Sheet

EN-Series - Valve Regulated Lead Acid Battery EN180-6

SPECIFICATIONS		
	6	V
Nominal voltage	180	Ah
10-hr rate Capacity to 10.8V at 20°C		
10-min rate Constant Power to 1.6V/cell at 20°C	800	Watts
DIMENSIONS	1	
Length	305 (±1)	mm
Width	210 (±1)	mm
Height	240 (±1)	mm
(height over terminals)	N/A	mm
Mass (typical)	35	kg
TERMINAL TYPE		
Threaded terminal - (M=Male or F=Female)	M8 (F)	mm
Torque	6 (±0.5)	Nm
OPERATING TEMPERATURE RANGE		
Storage (in fully charged condition)	-20°C to +50°C	
Charge	-15°C to +50°C	
Discharge	-20°C to +60°C	
STORAGE	1	
Capacity loss per month at 20°C (approx)	3	%
CASE MATERIAL		
Flame retardant	ABS (UL94:V0)	
CHARGE VOLTAGE		
Float charge voltage at 20°C	6.78 (±1%) 2.26 (±1%)	V V/cell
Float Charge voltage temperature correction factor (for variations from the standard 20°C)	-3	mV/cell/°C
Boost charge at 20°C	7.2 (±2%) 2.40 (±2%)	V V/cell
Boost Charge voltage temperature correction factor (for variations from the standard 20°C)	-4	mV/cell/°C
CHARGE CURRENT		
Float charge current limit	No limit	Α
Boost charge current limit	45	Α
MAXIMUM DISCHARGE CURRENT		
1 second	1500	Α
1 minute	960	Α
SHORT-CIRCUIT CURRENT & INTERNAL RESISTANCE		
(according to EN IEC 60896-21)		
Internal resistance	2.15	mΩ
Short-Circuit current	3235	Α
IMPEDANCE		
Measured at 1 kHz	1.7	mΩ
PERFORMANCE & CHARACTERISTICS		
PERFORMANCE & CHARACTERISTICS Refer to the technical manual	EN	
Refer to the technical manual	EN	
Refer to the technical manual DESIGN LIFE	EN -	
Refer to the technical manual DESIGN LIFE EUROBAT Classification: High Performance	-	vears
Refer to the technical manual DESIGN LIFE	- 12+ 12	years years

SAFETY Installation

Can be installed and operated in any orientation except permanently inverted

Handles

Batteries must not be suspended by their handles (where fitted)

Vent valves

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.


Gas Release

VRLA Batteries release hydrogen gas which can form explosive mixtures in air. Do not place inside a sealed container

Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations





3RD PARTY CERTIFICATIONS

ISO 9001 - Quality Management Systems
ISO 14001 - Environmental Management Systems
EN 18001 - OHSAS Management Systems
UNDERWRITERS LABORATORIES Inc.



STANDARDS

IEC61056 IEC60896-21/22







ALL DATA IS SUBJECT TO CHANGE WITHOUT NOTICE Issue No.: V.2 / Issue Date: March 2011



YUASA BATTERY SALES UK LTD. Unit 13, Hunts Rise South Marston Industrial Estate SN3 4TG